

100.0 kVA JOHN DEERE GENERATOR

FEATURES & BENEFITS

- Maximum 110.0 kVA, 400 V, 1500 RPM
- Industrial brushless alternator with AVR
- Steel baseframe, retention basin & fuel tank with sensor
- 160 litre tank for 9 hrs @ 75% Load
- Test report, manuals and electrical drawings supplied
- Modular design, open and silent version available
- Industrial silencer and coupling flange
- Electrical panel mounted on board the unit with digital control device installed in metal box
- Compact for easy handling and use
- World wide after sales service and technical support



GENERAL DATA	
Model:	JD100GXHD
Continuous power (PRP):	100.0 kVA
Continuous power (PRP):	80.0 kW
Stand-by power (LTP):	110.0 kVA
Stand-by power (LTP):	88.0 kW
Power factor:	0.8
Frequency (Hz):	50 Hz
Voltage (V):	400 V
Width:	1040 mm
Length:	2560 mm
Height:	1805 mm
Weight:	1590 kgs
Tank Capacity:	160 l
dBa @ 7m:	67.0 dBA

ALTERNATOR	
Alternator brand:	MARELLI
Alternator model:	MJB225MA4
L.T.P. Power:	116.0 kVA
P.R.P. Power:	105.0 kVA
Connection:	Series star
Phases:	Three phases with neutral
Terminal Number:	12
IP Protection:	23
Alternate Alternator:	STAMFORD / UCI274C

ENGINE DATA	
Brand:	JOHN DEERE
Model:	4045HF158
Cylinders:	4
RPM:	1500
Cubic Capacity:	4.50
Air Intake:	Turbocharged
Standard Voltage:	12
SAE:	3-11 1/2
BMEP:	1618
Cooling:	Water
Flywheel P.R.P. Power:	88.0 kW
Flywheel Stand-by Power:	96.5 kW
Oil Qty:	12.0 l
Antifreeze Qty:	8.5 l
Heat from Radiator:	38.0 kW
Heat from Exhaust:	74.0 kW
Exhaust Temperature:	545 °C
Cooling Airflow:	150.00 m ³ /min
Combustion Airflow:	6.40 m ³ /min
Exhaust Airflow:	17.00 m ³ /min
TA Luft / TA Luft 2:	Standard / Not available
Stage:	Not available

FUEL CONSUMPTION	
Fuel Cons. at 110%:	25.0 l/h
Fuel Cons. at 100%:	23.0 l/h
Fuel Cons. at 75%:	16.5 l/h
Fuel Cons. at 50%:	11.0 l/h
Fuel Cons. at 25%:	6.0 l/h

* Specs subject to change without prior notice.
 * Measurements based on ISO8528-1 Standards
 * Picture may vary from actual product.